

Step12

CODE SETTING AND DELETING

Factory default set Master Code is ★123456#. The code should be changed immediately upon installation. To set keypad codes, remove Code Cover.

A. MASTER CODE

- a. Push up switch 1 to **ON** position.

ON	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
OFF	<input type="checkbox"/>	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
	1	2	3	4

- b. Press ★ key and wait for two beeps.
 c. Press 123456 then # key.
 d. Enter new Master Code (4~8 digits) then # key.
 e. Return switch 1 to **OFF** position. Master Code has been changed.
 f. In normal operation mode all four switches are at **OFF** position.
 g. Confirm new Master Code is valid. Put Code Cover back.

ON	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
OFF	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
	1	2	3	4

• Please write down Master Code and keep in safe place. If Master Code is lost or forgotten, we will not be able to retrieve it for you.

B. SUB-CODE SETTING

User 1 Station:

- a. Push up switches 1 and 4 to **ON** position.
 b. Press ★ key and wait for two beeps then enter your Master code followed by # key.
 c. Enter User 1 Code (4~6 digits) then # key.
 d. Return switches 1 and 4 to **OFF** position (Back to operation mode).
 e. Confirm new user code is valid.

ON	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/>
OFF	<input type="checkbox"/>	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>
	1	2	3	4

C. SUB-CODE SETTING FOR OTHER USERS

Repeat above procedures using the station for each respective user.

User 2 Station

ON	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>
OFF	<input type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/>
	1	2	3	4

User 3 Station

ON	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
OFF	<input type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
	1	2	3	4

User 4 Station

ON	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/>
OFF	<input type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>
	1	2	3	4

User 5 Station

ON	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>
OFF	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/>
	1	2	3	4

User 6 Station

ON	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
OFF	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
	1	2	3	4

User 7 Station

ON	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
OFF	<input type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
	1	2	3	4

• Please write down each user's name that corresponds to each station.

D. DELETING SUB-CODES

- a. Set station for user you wish to delete.
 b. Press ★ Master Code #, wait for three beeps, and # again.
 c. Return switches to normal operation mode and put Code Cover back.